# **Definitions M - N**

### M2M Flowgate:

"M2M Flowgate" shall have the meaning provided in the Joint Operating Agreement between the Midcontinent Independent Transmission System Operator, Inc. and PJM Interconnection, L.L.C.

### Maintenance Adder:

"Maintenance Adder" shall mean an adder that may be included to account for variable operation and maintenance expenses in a Market Seller's Fuel Cost Policy. The Maintenance Adder is calculated in accordance with the applicable provisions of PJM Manual 15, and may only include expenses incurred as a result of electric production.

### Market Buyer:

"Market Buyer" shall mean a Member that has met reasonable creditworthiness standards established by the Office of the Interconnection and/or PJMSettlement in Tariff, Attachment Q, and that is otherwise able to make purchases in the PJM Interchange Energy Market.

### Market Monitoring Unit or MMU:

"Market Monitoring Unit" or "MMU" shall mean the independent Market Monitoring Unit defined in 18 CFR § 35.28(a)(7) and established under the PJM Market Monitoring Plan (Attachment M) to the PJM Tariff that is responsible for implementing the Market Monitoring Plan, including the Market Monitor. The Market Monitoring Unit may also be referred to as the IMM or Independent Market Monitor for PJM.

### **Market Operations Center:**

"Market Operations Center" shall mean the equipment, facilities and personnel used by or on behalf of a Market Participant to communicate and coordinate with the Office of the Interconnection in connection with transactions in the PJM Interchange Energy Market or the operation of the PJM Region.

### **Market Participant:**

"Market Participant" shall mean a Market Buyer, a Market Seller, and/or an Economic Load Response Participant, except when that term is used in or pertaining to Tariff, Attachment M, Tariff, Attachment Q, Operating Agreement, section 15, Tariff, Attachment K-Appendix, section 1.4 and Operating Agreement, Schedule 1, section 1.4. "Market Participant," when such term is used in Tariff, Attachment M, shall mean an entity that generates, transmits, distributes, purchases, or sells electricity, ancillary services, or any other product or service provided under the PJM Tariff or Operating Agreement within, into, out of, or through the PJM Region, but it shall not include an Authorized Government Agency that consumes energy for its own use but does not purchase or sell energy at wholesale. "Market Participant," when such term is used in or pertaining to Tariff, Attachment Q, Operating Agreement, section 15, Tariff, Attachment K-Appendix, section 1.4 and Operating Agreement, Schedule 1, section 1.4, shall mean a Market Buyer, a Market Seller, an Economic Load Response Participant, an FTR Participant, a Capacity Market Buyer, or a Capacity Market Seller.

# Market Participant Energy Injection:

"Market Participant Energy Injection" shall mean transactions in the Day-ahead Energy Market and Real-time Energy Market, including but not limited to Day-ahead generation schedules, realtime generation output, Increment Offers, internal bilateral transactions and import transactions, as further described in the PJM Manuals.

# Market Participant Energy Withdrawal:

"Market Participant Energy Withdrawal" shall mean transactions in the Day-ahead Energy Market and Real-time Energy Market, including but not limited to Demand Bids, Decrement Bids, real-time load (net of Behind The Meter Generation expected to be operating, but not to be less than zero), internal bilateral transactions and Export Transactions, as further described in the PJM Manuals.

# Market Seller:

"Market Seller" shall mean a Member that has met reasonable creditworthiness standards established by the Office of the Interconnection and/or PJMSettlement in Tariff, Attachment Q, and that is otherwise able to make sales in the PJM Interchange Energy Market.

## **Maximum Emergency:**

"Maximum Emergency" shall mean the designation of all or part of the output of a generating unit for which the designated output levels may require extraordinary procedures and therefore are available to the Office of the Interconnection only when the Office of the Interconnection declares a Maximum Generation Emergency and requests generation designated as Maximum Emergency to run. The Office of the Interconnection shall post on the PJM website the aggregate amount of megawatts that are classified as Maximum Emergency.

## **Maximum Generation Emergency:**

"Maximum Generation Emergency" shall mean an Emergency declared by the Office of the Interconnection to address either a generation or transmission emergency in which the Office of the Interconnection anticipates requesting one or more Generation Capacity Resources, or Non-Retail Behind The Meter Generation resources to operate at its maximum net or gross electrical power output, subject to the equipment stress limits for such Generation Capacity Resource or Non-Retail Behind The Meter resource in order to manage, alleviate, or end the Emergency.

## **Maximum Daily Starts:**

"Maximum Daily Starts" shall mean the maximum number of times that a generating unit can be started in an Operating Day under normal operating conditions.

### **Maximum Generation Emergency Alert:**

"Maximum Generation Emergency Alert" shall mean an alert issued by the Office of the Interconnection to notify PJM Members, Transmission Owners, resource owners and operators, customers, and regulators that a Maximum Generation Emergency may be declared, for any Operating Day in either, as applicable, the Day-ahead Energy Market or the Real-time Energy Market, for all or any part of such Operating Day.

### **Maximum Run Time:**

"Maximum Run Time" shall mean the maximum number of hours a generating unit can run over the course of an Operating Day, as measured by PJM's State Estimator.

### Maximum Weekly Starts:

"Maximum Weekly Starts" shall mean the maximum number of times that a generating unit can be started in one week, defined as the 168 hour period starting Monday 0001 hour, under normal operating conditions.

### Member:

"Member" shall mean an entity that satisfies the requirements of Operating Agreement, section 11.6 and that (i) is a member of the LLC immediately prior to the Effective Date, or (ii) has executed an Additional Member Agreement in the form set forth in Operating Agreement, Schedule 4.

### **Members Committee:**

"Members Committee" shall mean the committee specified in Operating Agreement, section 8, composed of representatives of all the Members.

### **Minimum Generation Emergency:**

"Minimum Generation Emergency" shall mean an Emergency declared by the Office of the Interconnection in which the Office of the Interconnection anticipates requesting one or more generating resources to operate at or below Normal Minimum Generation, in order to manage, alleviate, or end the Emergency.

### **Minimum Down Time:**

For all generating units that are not combined cycle units, "Minimum Down Time" shall mean the minimum number of hours under normal operating conditions between unit shutdown and unit startup, calculated as the shortest time difference between the unit's generator breaker opening and after the unit's generator breaker closure, which is typically indicated by telemetered or aggregated State Estimator megawatts greater than zero. For combined cycle units, "Minimum Down Time" shall mean the minimum number of hours between the last generator breaker opening and after first combustion turbine generator breaker closure, which is typically indicated by telemetered or aggregated State Estimator megawatts greater than zero.

# **Minimum Run Time:**

For all generating units that are not combined cycle units, "Minimum Run Time" shall mean the minimum number of hours a unit must run, in real-time operations, from the time after generator breaker closure, which is typically indicated by telemetered or aggregated State Estimator megawatts greater than zero, to the time of generator breaker opening, as measured by PJM's State Estimator. For combined cycle units, "Minimum Run Time" shall mean the time period after the first combustion turbine generator breaker closure, which is typically indicated by telemetered or aggregated State Estimator breaker closure, which is typically indicated by telemetered or aggregated by PJM's State Estimator megawatts greater than zero, and the last generator breaker opening as measured by PJM's State Estimator.

# MISO:

"MISO" shall mean the Midcontinent Independent System Operator, Inc. or any successor thereto.

# **Multi-Driver Project:**

"Multi-Driver Project" shall mean a transmission enhancement or expansion that addresses more than one of the following: reliability violations, economic constraints or State Agreement Approach initiatives.

# NERC:

"NERC" shall mean the North American Electric Reliability Corporation, or any successor thereto.

## **NERC Functional Model:**

"NERC Functional Model" shall be the set of functions that must be performed to ensure the reliability of the electric bulk power system. The NERC Reliability Standards establish the requirements of the responsible entities that perform the functions defined in the Functional Model.

## **NERC Interchange Distribution Calculator:**

"NERC Interchange Distribution Calculator" shall mean the NERC mechanism that is in effect and being used to calculate the distribution of energy, over specific transmission interfaces, from energy transactions.

### NERC Reliability Standards:

"NERC Reliability Standards" shall mean those standards that have been developed by NERC and approved by FERC to ensure the reliability of the electric bulk power system.

**NERC Rules of Procedure:** "NERC Rules of Procedure" shall be the rules and procedures developed by NERC and approved by the FERC. These rules include the process by which a responsible entity, who is to perform a set of functions to ensure the reliability of the electric bulk power system, must register as the Registered Entity.

### Net Benefits Test:

"Net Benefits Test" shall mean a calculation to determine whether the benefits of a reduction in price resulting from the dispatch of Economic Load Response exceeds the cost to other loads resulting from the billing unit effects of the load reduction, as specified in Operating Agreement, Schedule 1, section 3.3A.4 and the parallel provisions of Tariff, Attachment K-Appendix, section 3.3A.4.

### **Network Resource:**

"Network Resource" shall have the meaning specified in the PJM Tariff.

### **Network Service User:**

"Network Service User" shall mean an entity using Network Transmission Service.

### **Network Transmission Service:**

"Network Transmission Service" shall mean transmission service provided pursuant to the rates, terms and conditions set forth in Tariff, Part III, or transmission service comparable to such service that is provided to a Load Serving Entity that is also a Transmission Owner.

## New York ISO or NYISO:

"New York ISO" or "NYISO" shall mean the New York Independent System Operator, Inc. or any successor thereto.

## **No-load Cost:**

"No-load Cost" shall mean the hourly cost required to <u>theoretically operate a synchronized unit</u> at zero MW. It consists primarily of the cost of fuel, as determined by the unit's no load heat (adjusted by the performance factor) times the fuel cost. It also includes operating costs, <u>maintenance adders</u>, and emissions allowances.create the starting point of a monotonically increasing incremental offer curve for a generating unit.

### **Non-Disclosure Agreement:**

"Non-Disclosure Agreement" shall mean an agreement between an Authorized Person and the Office of the Interconnection, pursuant to Operating Agreement, section, the form of which is appended to this Agreement as Operating Agreement, Schedule 10, wherein the Authorized Person is given access to otherwise restricted confidential information, for the benefit of their respective Authorized Commission.

### Non-Dispatched Charging Energy:

"Non-Dispatched Charging Energy" shall mean all Direct Charging Energy that an Energy Storage Resource Model Participant receives from the electric grid that is not otherwise Dispatched Charging Energy.

### Nonincumbent Developer:

"Nonincumbent Developer" shall mean: (1) a transmission developer that does not have an existing Zone in the PJM Region as set forth in Tariff, Attachment J; or (2) a Transmission Owner that proposes a transmission project outside of its existing Zone in the PJM Region as set forth in Tariff, Attachment J.

### **Non-Regulatory Opportunity Cost:**

"Non-Regulatory Opportunity Cost" shall mean the difference between (a) the forecasted cost to operate a specific generating unit when the unit only has a limited number of starts or available run hours resulting from (i) the physical equipment limitations of the unit, for up to one year, due to original equipment manufacturer recommendations or insurance carrier restrictions, (ii) a fuel supply limitation, for up to one year, resulting from an event of Catastrophic Force Majeure; and, (b) the forecasted future Locational Marginal Price at which the generating unit could run while not violating such limitations. Non-Regulatory Opportunity Cost therefore is the value associated with a specific generating unit's lost opportunity to produce energy during a higher valued period of time occurring within the same period of time in which the unit is bound by the referenced restrictions, and is reflected in the rules set forth in PJM Manual 15. Non-Regulatory Opportunity Costs shall be limited to those resources which are specifically delineated in Operating Agreement, Schedule 2.

## Non-Retail Behind The Meter Generation:

"Non-Retail Behind The Meter Generation" shall mean Behind the Meter Generation that is used by municipal electric systems, electric cooperatives, and electric distribution companies to serve load.

### **Non-Synchronized Reserve:**

"Non-Synchronized Reserve" shall mean the reserve capability of non-emergency generation resources that can be converted fully into energy within ten minutes of a request from the Office of

the Interconnection dispatcher, and is provided by equipment that is not electrically synchronized to the Transmission System.

## Non-Synchronized Reserve Event:

"Non-Synchronized Reserve Event" shall mean a request from the Office of the Interconnection to generation resources able and assigned to provide Non-Synchronized Reserve in one or more specified Reserve Zones or Reserve Sub-zones, within ten minutes to increase the energy output by the amount of assigned Non-Synchronized Reserve capability.

### **Non-Variable Loads:**

"Non-Variable Loads" shall have the meaning specified in Operating Agreement, Schedule 1, section 1.5A.6, and the parallel provisions of Tariff, Attachment K-Appendix, 1.5A.6.

### Normal Maximum Generation:

"Normal Maximum Generation" shall mean the highest output level of a generating resource under normal operating conditions.

### Normal Minimum Generation:

"Normal Minimum Generation" shall mean the lowest output level of a generating resource under normal operating conditions.